

# CG1250



## Cummins Silent Generator

### Performance

- Carefully selected components
- Accurately developed and tested configuration

### Quality Control

- International standard testing procedure
- Professional manufacture team

### Service efficiency

- Humanization design and improvements
- Superior accessibility to all service points

### Increased transport efficiency

- Compact and safe concept
- Sturdy design

### Superior resale value

- Designed and built to last

## Technical Data

Genset Model		CG1250
Frequency		50 Hz
Rated speed	r/min	1500 rpm
Rated power factor (lagging)		0.8
Rated prime power	kVA	1250/1000
Rated standby power	kVA	1375/1100
Rated voltage line to line	V	380/220
Rated current	A	1899.2
Maximum sound power level	dB(A)	75
Fuel consumption at 75%	L/H	181
Fuel consumption at 100%	L/H	214
Fuel tank capacity	L	1500

Engine Model		KTA38-G5
Rated net power prime	kW	1097
Rated net power standby	kW	1227
Cooling way		Water
Number of cylinders		6
Arrangement		In-line
Bore & Stroke	mm	159x159
Compression ratio		14.5:1
Displacement	L	50.3
Oil capacity	L	177
Charging alternator	V	24
Start motor	V	24

### Alternator-Stamford

<b>Model</b>		<b>LV634E</b>
Voltage	V	380/220
Frequency	Hz	50
Prime Capacity	kVA	1000
Prime Power	kW	800
Power input	kW	840
Phase no.		3
Power factor		0.8
Voltage regulation	%	±0.5
Protection grade		IP23
Insulation grade		Class H

### Dimension

Length*width*height	mm	40HQ container
Net weight	kg	11000
Gross weight	kg	11100



### Controller-Deepsea DSE3110

<b>Standard function</b>	
Engine control	Generator monitoring
Generator protection	Specification display
<b>Display</b>	
Frequency	Battery voltage
Running hour	
<b>Warning/shutdown</b>	
Under/over voltage	Under/over speed
Under/over frequency	Low oil pressure
High/low battery voltage	High water temperature
<b>Communication modules</b>	
USB	



### Controller-Deepsea DSE6020

<b>Standard function</b>	
Engine control	Generator monitoring
Generator protection	Specification display
<b>Display</b>	
Voltage	Current
Frequency	Fuel level
Oil pressure	Rated power
Running hour	Battery voltage
<b>Warning/shutdown</b>	
Under/over voltage	Under/over speed
Under/over frequency	Low oil pressure
High/low battery voltage	High water temperature
<b>Communication modules</b>	
RS232, RS485, S-USB	

*This generator does comply with EU requirements related to working environment, regulations concerning safety and emissions as well with the outdoor noise directive 2000/14/EC.*

## PT. SURYA PUTRA MESINDO

**Address :** Jl. Kamal Raya Outer Ring Road,  
Taman Palem Lestari, Ruko Galaxy Blok N No.17,18,19  
Cengkareng - Jakarta Barat 11730 INDONESIA  
Phone : (021) 5595-9133 (Hunting)  
Fax : (021) 5595-9132  
E-mail : [suryaputra@indo.net.id](mailto:suryaputra@indo.net.id)  
Website : [www.suryaputra.co.id](http://www.suryaputra.co.id)